



VIVAX
METROTECH

VM-810

Technical Specifications V2.3



Worldwide Locations

World Headquarters, United States of America

Vivax-Metrotech Corporation

3251 Olcott Street, Santa Clara, CA 95054, USA

T/Free : 1-800-446-3392

Tel : +1-408-734-1400

Fax : +1-408-734-1415

Website: www.vivax-metrotech.com

Email : SalesUSA@vxmt.com

Central/South America and the Caribbean

Ventas para América Latina

3251 Olcott Street, Santa Clara, CA 95054, USA

T/Free : 1-800-446-3392

Tel : +1-408-734-1400

Fax : +1-408-743-5597

Website: www.vivax-metrotech.com

Email : LatinSales@vxmt.com

Canada

Vivax Canada, Inc.

41 Courtland Ave Unit 8, Vaughan, ON L4K 3T3, Canada

Tel : +1-289-846-3010

Fax : +1-905-752-0214

Website: www.vivax-metrotech.ca

Email : SalesCA@vxmt.com

United Kingdom

Vivax-Metrotech Ltd.

Unit 1, B/C Polden Business Centre, Bristol Road, Bridgwater, Somerset, TA6 4AW, UK

Tel : +44(0)1793 822679

Website: www.vivax-metrotech.co.uk

Email : SalesUK@vxmt.com

France

Vivax-Metrotech SAS

Technoparc - 1 allée du Moulin Berger, 69130 Ecully, France

Tel : +33(0)4 72 53 03 03

Fax : +33(0)4 72 53 03 13

Website: www.vivax-metrotech.fr

Email : SalesFR@vxmt.com

Germany

Metrotech Vertriebs GmbH

Am steinernen Kreuz 10a
96110 Schesslitz, Germany

Tel : +49 954 277 227 43

Website: www.vivax-metrotech.de

Email : SalesEU@vxmt.com

China

Vivax-Metrotech (Shanghai) Ltd.

3/F No.90, Lane 1122 Qinzhou Rd.(N),
Shanghai, China 200233

Tel : +86-21-5109-9980

Fax : +86-21-2281-9562

Website: www.vivax-metrotech.com

Email : SalesCN@vxmt.com.cn

A. Description and Typical Applications

Item	Parameter	
Model Number	VM-810 Receiver	VM-810 Transmitter
	VX213-01	VX213-02
Description	Single high-frequency locator receiver and transmitter	
Uses	Locating & pinpointing the position of buried pipes and cables	

B. Receiver Characteristics

Item	Parameter	
Construction	<ul style="list-style-type: none"> - High-impact thermoplastic (ABS) injection molded housing - Retractable aluminum antenna tube 	
Weight	3.1lbs (1.4kg)	
Dimensions	Collapsed: 22in(L) x 8.3in(W) x 11in(H) (560mm x 210mm x 280mm) Extended: 31.1in(L) x 8.3in(W) x 11in(H) (790mm x 210mm x 280mm)	
Display Type	Black & white TFT 2.7" LCD WQVGA display (400 x 240 pixels)	
Receiver Antennas	3 x Peak antennas, 1 x compass antenna	
Batteries	2 x D-Cell alkaline batteries	
Battery Life	Typically 65 hours of continuous use at 70°F (21°C)	
Environmental	IP54 and NEMA 4	
Manufacturing	Designed and manufactured per ISO 9001:2015	
External Connectors	<ul style="list-style-type: none"> - 1 x 3.5mm Headphone jack - 1 x Mini USB socket for software update - 1 x 4-pin Accessory jack 	
Temperature Range	Operating: -4°F to 122°F (-20°C to 50°C)	
Compliance/Approvals	<ul style="list-style-type: none"> - Complies with European standard CE (Directive 99/5/EC) <ul style="list-style-type: none"> • EN 55011 • EN 61000-4-2 • EN 61000-4-3 • EN 61000-4-8 	<ul style="list-style-type: none"> - Complies with FCC Rules Part 15 <ul style="list-style-type: none"> • CFR 47 Part 15: 2006
What's In the Box	<ul style="list-style-type: none"> - VM-810 Receiver - Hard case - Mini-USB cable 	<ul style="list-style-type: none"> - 2 x Alkaline D-Cell batteries - User handbook

Compatible Accessory Options	<ul style="list-style-type: none"> - D22 Sonde, 8ft/2.4m depth range – 83kHz - D38 Sonde, 16.3ft/5m depth range – 83kHz - D64 Sonde, 26ft/8m depth range – 83kHz - Headphones with 3.5mm jack
-------------------------------------	-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------

C. Receiver Operational

Item	Parameter								
Information Displayed	<ul style="list-style-type: none"> - Signal strength: Numeric value - Distance-sensitive Left/Right Centerline offset needle indicator - Compass: +/- 90° line direction indicator - Battery indicator - Depth and current reading 								
Audio Indication	<ul style="list-style-type: none"> - Tones for Left or Right - Fading when close to the centerline - Silence when centered or the signal is too weak 								
Configuration	Easy One-button operation: <ul style="list-style-type: none"> - Automatic backlight control - Short press – On - Long press – Off - Short press when the unit is switched On – Depth and Current reading 								
Operating Frequencies	83.1kHz (83,077.5 Hz)								
Operating Modes	<ul style="list-style-type: none"> - Peak locate - Sonde 								
Gain / Scaling Control	Automatic Gain control								
Performance Using Single Undistorted Signal Source	<table border="1" style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 50%;">Trace accuracy:</td> <td>- Distance Sensitive Left/Right Guidance™</td> </tr> <tr> <td>Current measurement accuracy:</td> <td> <ul style="list-style-type: none"> - 5% of actual current – up to 10ft (3m) - 10% of actual current – up to 20ft (6m) </td> </tr> <tr> <td>Depth measurement accuracy:</td> <td> <ul style="list-style-type: none"> - 10 feet (3m): +/-5% or 2" - 20 feet (10m): +/-10% </td> </tr> <tr> <td colspan="2">Depth range: Dependent on the strength of the signal radiating to the locator</td> </tr> </table>	Trace accuracy:	- Distance Sensitive Left/Right Guidance™	Current measurement accuracy:	<ul style="list-style-type: none"> - 5% of actual current – up to 10ft (3m) - 10% of actual current – up to 20ft (6m) 	Depth measurement accuracy:	<ul style="list-style-type: none"> - 10 feet (3m): +/-5% or 2" - 20 feet (10m): +/-10% 	Depth range: Dependent on the strength of the signal radiating to the locator	
Trace accuracy:	- Distance Sensitive Left/Right Guidance™								
Current measurement accuracy:	<ul style="list-style-type: none"> - 5% of actual current – up to 10ft (3m) - 10% of actual current – up to 20ft (6m) 								
Depth measurement accuracy:	<ul style="list-style-type: none"> - 10 feet (3m): +/-5% or 2" - 20 feet (10m): +/-10% 								
Depth range: Dependent on the strength of the signal radiating to the locator									
Compatible with Transmitters	810 Classic, 810DX and VM-810Tx								

A. Transmitter Characteristics

Item	Parameter
Construction	High-impact thermoplastic (ABS) injection molded housing
Weight	2.95 lbs (1.34kg)
Dimension	9.4in(L) x 4.6in(W) x 7.2in(H) (239mm x 117mm x 182 mm)
Power Options	Standard battery pack - using 6 x alkaline "D" cells
Battery Life	At 70°F (21°C) - continuous use Output Power Alkaline 1 watt > 60 hours
Environmental	IP54 and NEMA 4
Manufacturing	Designed and manufactured per ISO 9001:2015
External Connectors	3-pin XLR connection socket
Temperature Range	Operating : -4°F to 122°F (-20°C to 50°C) Storage : -40°F to 140°F (-40°C to 60°C)
Compliance and Approvals	<ul style="list-style-type: none"> - Complies with European standard CE (Directive 99/5/EC) <ul style="list-style-type: none"> • EN 55011 • EN 61000-4-2 • EN 61000-4-3 • EN 61000-4-8 - Complies with FCC Rules Part 15 <ul style="list-style-type: none"> • CFR 47 Part 15
What's In the Box	<ul style="list-style-type: none"> - VM-810 Transmitter - 1 x direct connection lead (XLR plug on two (red/black) 10ft (3.5m) long cables with crocodile clips) - 1 x Ground stake - Transmitter shoulder strap - 4 x Alkaline D-Cell batteries
Compatible Accessories Options	<ul style="list-style-type: none"> - 2in (50mm) transmitter clamp - 4in (100mm) transmitter clamp - 5in (125mm) transmitter clamp - 18in (455mm) transmitter clamp - Live Plug Connector - Live Cable Connector - Ground Extension Spool - Telco Clip Connection Lead

B. Transmitter Operational

Item	Parameter
Location Modes	- Induction mode – applies signal inductively using the internal antenna

	<ul style="list-style-type: none"> - Direct connection mode - applies signal directly to the cable by clipping one output lead to the cable, the other to an independent ground - Clamp mode – applies signal using an inductive clamp (toroid) that is placed around the target cable <p>* Modes are automatically selected when an accessory is plugged in. * Default mode (no accessories) is induction.</p>
Transmitting Frequency by Mode	- Induction mode / Direct connection mode / Clamp mode: 83.1kHz (83,077.5Hz)
Transmitting Mode Power output	In accordance with FCC part 15: <ul style="list-style-type: none"> - 1 watt – in High output level - 1/3 watt – in Low output level
Maximum Output Voltage	Maximum output voltage = 60V RMS
Maximum Output Current	Maximum output current = 150mA RMS constant power
Output Protection	Output protected against accidental connection to up to 240V AC (50/60Hz)
Audio indication	<ul style="list-style-type: none"> - Connection quality – variable beep rate sound showing the better signal applied - Low battery warning
Controls	Use pushbuttons to select: <ul style="list-style-type: none"> - Power button: On / Off - Output level button: Low / High - Audio button: Off / Low / High
Compatible Receivers	VM-810, 810DX, 810 classic

C. Shipping and Packaging (Full Kit)

Item	Parameter
Shipping Weight	18.7lbs (8.5kg) (Full Kit)
Shipping Dimension	26in(L) x 12.2in(W) x 18.1in(H) (660mm x 310mm x 460mm) (estimation)

D. Warranty

Item	Parameter
Warranty	Receiver and Transmitter -12 months (Limited warranty)

Disclaimer: Product and accessory specification and availability information are subject to change without prior notice.